# TLA-300Series Line Array Column Speaker






**TLA Series (True Line Array)** Line Array Speaker System Center A Wonderful Integration of Art and Technology Create a New Model for Intelligent line array speaker system. Sound System not only provides high-quality sound, but also needs to more attractively integrate the business environment and more easily to combine speaker system.


#### **Feature**

- Italian made 3" high quality and sound pressure transducers.
- Solid and excellent mid range frequency response.
- Elegant aesthetic design for the most demanding installations.
- Plug and play smart Jack connector.
- Phoenix and Speakon Input for both portable and installation Applications.
- Supports multiple entertain for Dinner party, Hotel ball room, Bar, Shopping mall, Portable sound reinforcement.

#### **Specifications**

Model	TLA-306	TLA-312
Transducer	6 x 3" (75 mm) ferrite driver	12 x 3" (75 mm) ferrite driver
Frequency Respons	130Hz-20kHz	120Hz-18kHz
Rated Power	120W	240W
Sensitivity	95dB	97dB
Maximum SPL	123dB	127dB
Nominal Impedance	12Ω	6Ω
Dispersion Angle	100° x 20°	100° x 15°
Connection	2 x PHOENIX , 2 x Speakon connector	2 x PHOENIX , 2 x Speakon connector
Dimensions (W x H x D)	124 x 545 x 152 mm	124 x 1038 x 152 mm
Net Weight	6.6 kg	12 kg





SOUNDVISION Line Array Speaker

# **TLA-300Series Line Array Column Speaker**

### Applied to use with the Active Subwoofer TLA-12S / TLA-15S



Three Channels Output DSP Digital Signal Processing 600W/1000W for Bass Output Volume Control for Bass Boost enhanced 350W/500W for Full Range Output.

- 12",15" high quality and sound pressure transducers.
- Solid and excellent Low frequency response.
- Plug and play smart Jack connector.
- Separated Full range and Bass Volume control.
- Bluetooth connected music playback Applications.

### **Optional Accessories**

MP-35-60 (Long Standing with Cable Connection Inside 600mm)



MP-35-10 (Short Connector with Cable Connection Inside 100mm)

TM-1 (Wall-Mount Rack)



### **Typical Combinations**



TLA-312x 2 TLA-15S x 2



TLA-306 x 4 TLA-15S x 2



TLA-306 x 4 TLA-12S x 4

SOUNDVISION TLA Series True Line Array